

A Research paper on the Significance of Digital Frequency Relays in Grid Synchronization Maintenance

Md. Rakibul Hasan¹, Saikat Barua²

Department of Computer Science Engineering

Islamic University (IU), Bangladesh^{1,2}

Corresponding Authors' Email: - rhp.rakibul7@gmail.com ¹saikat021112035@gmail.com²

Abstract

Modeling tools play a crucial role in both educational and industrial settings, enabling engineers to simulate power systems under various operating conditions, including normal and faulty scenarios. This research focuses on the design of a relay system capable of addressing both over and under frequency conditions. Digital relays exhibit distinct advantages over traditional electromechanical relays, notably in terms of accuracy and response speed.

The significance of frequency control cannot be overstated, as significant fluctuations can potentially lead to complete power system blackouts. Historical incidents have demonstrated the severe consequences of frequency instability, often stemming from supply-demand imbalances and unforeseen contingencies. With the rise of distributed generation and the inherent challenges of islanding in modern power systems, the attention of both industrialists and researchers has once again turned to frequency relaying solutions.

This study aims to evaluate the performance of the proposed digital frequency relay under diverse system dynamics using simulation tools such as MATLAB/Simulink and microcontroller-based implementations. By conducting rigorous testing and analysis, this research endeavors to contribute to the enhancement of grid stability and the prevention of power system disruptions caused by frequency deviations.

Keywords: *Digital Frequency Relays, Grid Synchronization, Power Grid Maintenance, Frequency Protection, Electrical Grid, Relay Technology, Grid Stability, Grid Resilience, Frequency Deviations*

INTRODUCTION

In the present day, it's nearly impossible to imagine a single day without access to electricity. The power sector is instrumental in ensuring uninterrupted power supply to meet our daily needs. Within this sector, grid synchronization stands as an essential requirement for maintaining the seamless distribution of power. A key element in achieving grid synchronization is the management of electrical frequency.

This article delves into the concept of grid synchronization, shedding light on its significance in the realm of power distribution. We will explore the intricacies of parallel operation within power systems, the conditions necessary for such operations, and the advantages that grid synchronization brings to the table. Additionally, we will also touch upon the role of microcontrollers in this context, highlighting their relevance and impact in modern power management systems.

Objectives

Precision in Measurement, Enhanced Security, and Expedited Operations:

- The primary objective of digital frequency relays is to deliver precise measurements, ensuring the accuracy of the power system's data.
- They also bolster security measures, safeguarding critical grid operations against potential threats or faults.
- Furthermore, these relays are designed for speed, facilitating faster decision-making and response times in managing grid conditions.

Grid Power Assurance:

- Another pivotal goal of digital frequency relays is to ensure the stability and continuity of power within the grid.
- By monitoring and controlling frequency deviations, these relays play a key role in preventing grid disruptions and blackouts.

Accurate and Secure Protection for Frequency Anomalies:

- Digital frequency relays are engineered to provide accurate and dependable protection in scenarios involving under-frequency and over-frequency system conditions.
- They act as a critical safety net, swiftly identifying and mitigating frequency-related issues to maintain grid integrity and reliability.

Grid Synchronization

In the context of an alternating current electric power system, grid synchronization entails the critical procedure of aligning the speed and frequency of a power source, be it a generator or another supplier, with that of the existing network. Notably, it is essential to recognize that an alternator's ability to supply power to an electrical grid hinge upon it operating at the identical frequency as the network itself. This synchronization process serves as the foundational link for the effective integration of power sources into the operational grid.

WHY PARALLEL OPERATION**Continuity of Service:**

One of the primary reasons for implementing parallel operation in power systems is to ensure uninterrupted service. By connecting multiple power sources or generators in parallel, if one unit encounters a problem or needs maintenance, the others can seamlessly pick up the load, preventing disruptions in power supply. This redundancy is vital for critical applications where downtime is not acceptable.

Efficiency:

Parallel operation enhances the overall efficiency of a power generation system. When multiple generators operate in parallel, they can collectively handle varying load demands more efficiently. This means that generators can operate closer to their optimal load levels, reducing fuel consumption and operational costs. Improved efficiency is crucial for both economic and environmental reasons.

Maintenance and Repair:

Parallel operation simplifies maintenance and repair procedures. If one generator needs servicing, it can be taken offline without interrupting the supply. This flexibility minimizes

downtime and allows for scheduled maintenance activities to be carried out without affecting the power grid's reliability.

Increase Plant Capacity:

Parallel operation also enables the expansion of plant capacity when needed. Additional generators can be added to the system, increasing the overall capacity of the power plant. This scalability ensures that the power generation facility can adapt to growing demand or unexpected spikes in load, maintaining a balance between supply and demand in the grid.

Conditions for Parallel Operation

Four essential conditions must be met to facilitate parallel operation within a power system:

Voltage:

Voltage compatibility is paramount for parallel operation. All power sources or generators involved must produce voltages within a specified range and maintain a similar voltage magnitude. Ensuring voltage conformity prevents imbalances that could lead to undesirable current flows and potential equipment damage.

Frequency:

Frequency synchronization is equally critical. All generators operating in parallel must generate electricity at the same frequency. Maintaining consistent frequency levels is essential for avoiding phase mismatches and maintaining the integrity of the power supply.

Phase Sequence:

Phase sequence refers to the order in which the alternating current waveforms of different generators reach their peak values. In parallel operation, the phase sequences of all sources must align correctly to ensure that the combined output remains synchronized and that the loads receive power uniformly.

Phase Angle:

The phase angle represents the angular displacement between the alternating current waveforms of different generators. Parallel operation requires that these phase angles be coordinated to prevent issues like phase interference and potential short circuits. Proper phase

angle alignment ensures that the generators work harmoniously together in providing a stable power supply to the grid.

ADVANTAGES OF SYNCHRONIZATION

Increased Reliability:

Synchronization in power systems contributes significantly to enhanced reliability. By ensuring that multiple power sources or generators operate in harmony, the likelihood of service interruptions due to individual unit failures is minimized. This reliability is especially crucial for critical facilities, industries, and essential services that require a continuous power supply to function without disruptions.

Increased Flexibility:

Synchronization provides a notable boost to the flexibility of power generation and distribution. It allows for seamless integration of various power sources, such as renewable energy systems, backup generators, or multiple utility grids. This flexibility enables grid operators to adapt quickly to changing load demands, incorporate diverse energy sources, and maintain grid stability.

Reduced Maintenance Costs:

Implementing synchronization protocols can lead to reduced maintenance costs. By allowing generators to share the load efficiently, individual units are subject to less wear and tear. Additionally, scheduled maintenance can be performed without affecting power supply, minimizing downtime and associated expenses. Overall, this leads to cost savings for power system operators and end-users.

Economy:

The economic benefits of synchronization are substantial. Efficiently synchronized power systems can optimize the use of available resources, improving energy utilization. This, in turn, leads to cost savings for both power providers and consumers. Moreover, synchronization enables the integration of renewable energy sources, which can reduce dependence on fossil fuels and promote a more sustainable and economical energy landscape.

SYNCHRONIZATION LIMITS

Phase Angle (+/- 20 degrees):

Within a synchronized power system, maintaining a phase angle within the specified range of +/- 20 degrees is crucial. Deviations beyond this limit can disrupt the synchronization of generators and lead to phase mismatches, potentially causing electrical instability and equipment damage. Adhering to this phase angle constraint ensures harmonious operation.

Maximum Voltage Difference (-7%):

The maximum allowable voltage difference, typically limited to -7%, is a critical parameter for synchronization. Keeping voltage variations within this range is essential to prevent imbalances in the power distribution system. A voltage difference exceeding this limit can lead to overloading, voltage instability, and undesirable current flows.

Maximum Frequency (-0.44%):

The maximum permissible frequency deviation, often restricted to -0.44%, is another pivotal factor in synchronization. Consistency in frequency is vital for maintaining the uniform operation of generators and load equipment. A frequency exceeding this threshold can disrupt the synchronization process, potentially causing equipment damage and instability in the power grid. Staying within this frequency limit is crucial for grid reliability.

Alternator frequency & Grid frequency

The frequency of the sinusoidal voltage produced by the generator must be equal to the frequency of the sinusoidal voltage produced by the grid.

Alignment of Frequency:

A fundamental requirement in power generation and distribution is the synchronization of frequency. The frequency of the alternating current (AC) voltage generated by an alternator or generator must precisely match the frequency of the AC voltage produced by the electrical grid it connects to. This alignment ensures that the generated power seamlessly integrates with the existing grid supply.


Grid-Generator Harmony:

Ensuring the equality of frequencies between the alternator and the grid is essential for the harmonious operation of the entire power system. When these frequencies are not in sync, it

can lead to issues like phase mismatches, voltage instability, and ultimately, disruptions in the power supply.

Grid Frequency as a Reference:

Typically, the grid frequency serves as the reference point for generators. Generators are designed and controlled to produce electricity at the same frequency as the grid they are connected to. This coordination is critical for maintaining grid stability and the reliable delivery of electricity to consumers.



CONSEQUENCES OF SYNCHRONIZATION FAILURE

Circulating Current and Power Surges:

When synchronization between power sources is unsuccessful, it can result in circulating currents and power surges within the electrical system. These unwanted electrical phenomena can lead to inefficiencies, overheating, and potential damage to equipment and components.

Undesirable Rotor Oscillations:

Synchronization failure can cause undesirable rotor oscillations in generators. These oscillations can compromise the mechanical integrity of the rotating components, affecting the generator's performance and longevity.

System Imbalance:

A lack of synchronization can introduce imbalances within the power system. These imbalances may manifest as uneven distribution of loads and voltages, leading to unstable and unreliable power supply.

Circuit Breaker Tripping:

To prevent further complications and protect the grid, circuit breakers may trip in response to synchronization failure. This action isolates the faulty section of the electrical system, safeguarding the rest of the grid from potential damage or instability.

Alternator Shutdown:

Ultimately, if synchronization cannot be restored or maintained, the alternator or generator may shut down automatically to prevent further complications and protect the equipment from damage. This ensures the safety and integrity of the power generation system.

Why We Measure Frequency in the Power Grid:

Maintaining Generator Speed Consistency:

Frequency measurement is crucial for ensuring the consistent speed of generators. According to the formula $N_s = 120f/p$, where N_s represents the synchronous speed, f is the frequency, and p is the number of poles, any change in frequency directly impacts the generator's speed. To maintain a specific speed for generators, it is imperative to keep the frequency constant.

Synchronization Requirement:

Frequency measurement serves a critical role in power system synchronization. Both the grid frequency and the generator frequency must align perfectly for successful synchronization. When these frequencies deviate from each other, it can lead to issues, potentially causing generators to disconnect from the grid. To restore synchronization, adjustments are made to ensure that both frequencies match, allowing generators to reconnect and supply power seamlessly to the grid.

When the Alternator is out of Synchronism with the Grid

Alternator Slower than the Grid

If the alternator's rotational speed is slower than that of the grid it's attempting to connect to, it can lead to problematic scenarios. In this situation, the alternator effectively operates as a motor, and the grid exerts an effort to accelerate it to the required speed. This forced synchronization can subject the alternator to mechanical stress and potential damage, undermining its operational integrity.

Alternator Faster than the Grid:

Conversely, if the alternator operates at a speed faster than the grid, similar issues can arise. The grid, in this case, would endeavor to slow down the alternator to match its own frequency. This mismatch can result in excessive mechanical strains and adverse effects on the alternator's components, potentially leading to operational problems or even failure ensuring the precise synchronization of alternators with the grid is essential to prevent these scenarios and maintain the smooth and reliable operation of power generation systems.

EFFECTS OF LOAD CHANGES ON A SYNCHRONOUS ALTERNATOR**Increased Load - Decreased Frequency and Speed:**

When the electrical load on a synchronous alternator is increased, it experiences a decrease in both frequency and rotational speed. This phenomenon occurs because the alternator must work harder to meet the heightened demand for electrical power, leading to a natural reduction in speed and frequency.

Decreased Load - Increased Frequency and Speed:

Conversely, when the electrical load on the alternator is decreased, it results in an increase in both frequency and speed. With a reduced load, the alternator operates more efficiently, requiring less effort to generate power. As a result, the rotational speed and frequency tend to rise in response to the diminished load.

It's essential to note that while these tendencies occur when the load changes, synchronous alternators are designed to maintain a relatively constant speed and frequency for a specific, rated load. However, deviations from this rated load will lead to speed and frequency adjustments as the alternator adapts to the varying electrical demand.

Digital Frequency Relay and Its Applications

Digital frequency relay is a modern protection system, driven by microcontroller technology and equipped with software-based algorithms designed to detect electrical faults swiftly and accurately. Digital frequency relay is a MCU-based system with software-based protection algorithms for the detection of electrical faults.

APPLICATIONS OF DIGITAL FREQUENCY RELAY

Protection of the Power System:

A primary application of the digital frequency relay is to safeguard the power system from potential disruptions and damage. By continuously monitoring the frequency of the electrical grid, it can detect abnormalities and respond rapidly to protect the system from faults, short circuits, or other irregularities that could lead to power outages or equipment damage.

Preventing Blackouts:

One of the critical roles of the digital frequency relay is to prevent grid blackout events. In the event of a major generation or load loss, this relay acts as an essential safety net. It can detect significant deviations in frequency and initiate protective actions to stabilize the grid, helping to avert blackouts and ensure uninterrupted power supply to consumers.

Islanding Detection:

The digital frequency relay is also instrumental in identifying islanding operations. Islanding typically occurs when a section of the power system becomes electrically isolated from the main grid due to distributed generation or other factors. Detecting islanding is crucial for safety and grid stability. The relay can sense the loss of mains and respond by disconnecting or reconfiguring the isolated section to maintain synchronization with the main grid, ensuring a coordinated and secure power supply.

Modeling of Digital Frequency Relay

The Digital frequency relay consists of two parts

- ❖ Frequency Measuring Unit(FMU)
- ❖ Under-Over Frequency Detection Element (FDE).

FMU is used to measure the digital value of frequency from single phase line while FDE takes actions on over-Under frequency limit.






Fig9: Block Diagram for Implementing Over-Under Frequency Relay

IMPLEMENTATION OF DIGITAL FREQUENCY RELAY AND GRID SYNCHRONIZATION USING MATLAB SIMULINK :



Frequency Measure Unit (FMU):



- ❖ Hit Crossing' block is used to detect the zero crossing.
- ❖ The block passes the input signal at its zero crossings to the 'if' block, which in starts sending ramp signal to the output.
- ❖ The time duration of generated ramp is measured and saved to a variable 'A'.

- ❖ The variable A is stored in another variable B using the 'Transport Delay' block and the time of the next zero crossing is measured.
- ❖ Subtracting B from A at any instant will give half the time period whose value is held by the 'Sample and Hold' block, till the next zero crossing.
- ❖ The output (measured frequency) from FMU sends to the FDE for necessary tripping action, in case of fault.

Frequency Detection Element (FDE):

The digital relay has superiority over electromechanical relay in terms of accuracy and speed. This dissertation presents the design and various data conversion steps of a digital frequency relay. The designed relay will cover both over and under frequency conditions.





Fig 1.Over & Under Frequency Detection Block on SIMULINK

Flow Chart



Case-1

All alternators are running at same speed (Normal condition).





Fig2. Alternator 01, 02 & 03 (a) Relay status (b) 3phase voltage (c) 3phase current

Case 2:

Alternator 02 speed fall (Under frequency condition) and other alternators are running at same speed (Normal condition).





Fig3. Alternator 02 (a) Relay status (b) 3phase voltage (c) 3phase current





Fig4. Alternator 01 & 03 (a) Relay status (b) 3phase voltage (c) 3phase current

Case 3:

Alternator 02 speed increase (over frequency condition) and other alternators are running at same speed (normal condition).





Fig5. Alternator 02 (a) Relay status (b) 3phase voltage (c) 3phase current





Fig6. Alternator 01 & 03 (a) Relay status (b) 3phase voltage (c) 3phase current

Case-4 :

All alternators are running at same speed with over load.





Fig7. Alternator 01, 02 & 03 (a) Relay status (b) 3phase voltage (c) 3phase current

Hardware Implementations


Hardware Components for Implementation:

In the setup of a digital frequency relay system, various hardware components play vital roles in its operation and functionality. These components include:

- a) **Power Supply Block:** Provides the necessary electrical power to drive the entire system, ensuring proper functioning.
- b) **Micro-controller (Atmega32):** Serves as the central processing unit, executing control algorithms and coordinating the relay's response to frequency variations.
- c) **Relays:** Act as switches or control elements to open or close electrical circuits, enabling protective actions when frequency deviations are detected.
- d) **LCD (Liquid Crystal Display):** Offers a visual interface for monitoring and displaying relevant information about the relay's status and detected faults.
- e) **LED (Light Emitting Diode):** Provides visual indicators to signal specific system states or alarms, aiding in system monitoring and diagnostics.
- f) **Resistors and Capacitors:** Play essential roles in circuit design, controlling currents and voltages, and ensuring proper signal processing.
- g) **Diode (IN4007):** A diode component that can rectify and control the flow of electrical current within the system.
- h) **Optocoupler:** Used to isolate and protect sensitive components by electrically separating input and output circuits.
- i) **Timer (NE555):** Provides precise timing functions within the relay system, aiding in the accurate detection and response to frequency deviations.
- j) **BJT (Bipolar Junction Transistor, PN2222):** A transistor that may be used for signal amplification or switching functions within the relay circuitry.


These hardware components collectively form the infrastructure of a digital frequency relay system, allowing it to monitor, detect, and respond to frequency anomalies effectively in power systems

Power Supply Block



Microcontroller

A microcontroller (MCU) is a compact computing device integrated onto a single chip, purpose-built to manage and oversee specific functions within electronic systems. This miniature computer unit combines the essential elements of a central processing unit (CPU), memory storage, and input/output interfaces, efficiently handling tasks tailored to its designated application.



Pin Description of ATmega32A MCU

The ATmega32A microcontroller is equipped with a range of pins, each serving distinct functions within the device's operation. Understanding these pin descriptions is crucial for harnessing the capabilities of the MCU and interfacing it with external components and systems.

Relay Overview:

A relay serves as an electrical switch that operates via an electromagnetic mechanism. It comprises two main sets of terminals: input terminals for receiving one or more control signals and operating contact terminals. This versatile switch can feature varying numbers of contacts, available in different forms, including make contacts (which close when activated), break contacts (which open when activated), or combinations thereof. Relays play a pivotal role in controlling electrical circuits by enabling or interrupting the flow of current based on the input signals they receive.



Working Principle:

In this project, we've created a straightforward frequency relay using the ATmega32A microcontroller and the CODEVISION AVR compiler. This uncomplicated frequency relay is capable of measuring frequencies up to 8 MHz, thanks to the utilization of a 16 MHz clock for the ATmega32A microcontroller.

The underlying concept behind a frequency meter is quite simple: frequency, measured in Hertz (Hz), represents the number of cycles or pulses that occur in one second. The microcontroller (MCU) counts these pulses within a one-second interval to determine the frequency of the incoming signal. Here's a more detailed explanation:

Pulse Counting with Timer1:

We employ Timer1 on the ATmega32A to count the pulses of the incoming signal, which we want to measure for its frequency. These pulses are applied externally to the T1 pin2 (PB1) of the microcontroller. Timer1 operates in normal mode and begins counting the pulses when initiated.

Delay of One Second:

After starting the pulse count, the MCU introduces a delay of precisely one second.

Stopping Timer and Reading TCNT1:

At the end of the one-second interval, the MCU halts Timer1 and reads the value stored in the register TCNT1. This register contains the count of pulses that Timer1 accumulated during the one-second period.

Handling Timer Overflow:

In cases where Timer1 overflows, the MCU enables the overflow interrupt of Timer1. An overflow event signifies that Timer1 has completed 2^{16} counts (as it's a 16-bit register). Therefore, the MCU counts the number of such overflows occurring within one second.

Calculating Frequency:

With the number of overflows (denoted as 'i') counted within one second and the value stored in TCNT1, we can calculate the frequency using the following equation:

$$\text{Frequency} = i * 2^{16} + \text{TCNT1}$$


This equation accounts for the total number of pulses observed in one second.

Updating Frequency Reading:

The reading of the frequency meter is refreshed every one second, allowing for continuous monitoring and measurement of the input signal's frequency.


This project showcases a basic yet effective method for measuring frequency using an ATmega32A microcontroller, enabling applications where accurate frequency monitoring is essential.


BLOCK DIAGRAM





PROTEUS SIMULATION:

Under Frequency State








NORMAL FREQUENCY STATE




Over Frequency State




SINUSOIDAL SIGNAL, PULSATING DC SIGNAL AND ZERO CROSSING PULSE




Frequency Relay in Bus System




Hardware Setup



Top Part




Bottom Part



Various Signals Analysis & Initial Frequency:

Sinusoidal Signal




Pulsating DC Signal



Zero-Crossing Pulse




Initial Frequency




Under Frequency State


Measurement of Frequency & Rotational Speed



Normal Frequency State



Over Frequency State



BENEFITS:**Grid Power Security:**

One of the primary advantages of this project is its ability to enhance the security of the power grid. It ensures that power plants primarily supply electricity to the grid rather than drawing power from it, thus bolstering grid stability and reliability.

Accurate and Secure Protection:

The project offers precise and dependable protection mechanisms for under-frequency and over-frequency system conditions. This protection is crucial for preventing grid instability and blackouts due to frequency anomalies.

Enhanced Measurement and Security:

Additionally, the project provides accurate measurement capabilities, improving the precision of data collection. It also contributes to better security, dependability, and faster response times in managing grid operations.

LIMITATIONS:**Limited Alternator Integration:**

In the hardware setup, the project doesn't incorporate more than one alternator, whereas in the Simulink simulation, three alternators are used. This limitation could affect the system's representation in the hardware setup compared to the simulation.

RPM Measurement Inaccuracy:

The accuracy of RPM (rotations per minute) measurement is compromised due to the inherent speed instability of the machine. This limitation may affect the precision of certain measurements and control processes.

Need for Parasitic Resistive Load:

When employing synchronous machine blocks in Simulink, a small parasitic resistive load is necessary, connecting to the machine terminals. This load is required to mitigate numerical oscillations and ensure the stability of the simulation, introducing a minor complexity to the model.

FUTURE GOALS

Implementation of a Feedback System:

A key objective for the future is to incorporate a feedback system into this project. Feedback mechanisms can enhance the system's performance by continuously monitoring and adjusting its parameters in response to changing conditions. This will contribute to greater control and stability in managing power grid synchronization.

Integrated Multi-Measurement Device:

Another compelling future goal is the development of a comprehensive device capable of measuring multiple parameters simultaneously. This device would be designed to measure not only frequency but also voltage magnitude, phase sequence, and phase angle, all within a single integrated system. Such a multifunctional solution can provide a more holistic view of power system health and performance, offering valuable insights for grid operators and engineers.

CONCLUSION

In conclusion, this research paper underscores the vital role of digital frequency relays in maintaining grid synchronization, emphasizing their importance in preventing power system disruptions. The study outlines the objectives of digital relays, explores the intricacies of grid synchronization, and discusses the consequences of synchronization failure. The paper highlights the benefits of digital relays, including enhanced grid power security and accurate protection against frequency anomalies. It also acknowledges limitations such as limited alternator integration and RPM measurement inaccuracy. The future goals include implementing a feedback system and developing a multi-measurement device for comprehensive monitoring.

Overall, this research contributes to the understanding of grid synchronization and sets the stage for advancements in digital frequency relay technology, aiming to improve the resilience and reliability of power grids in the face of evolving challenges.

REFERENCE BOOK

1. Power system – by BR Gupta

2. <https://pdfcoffee.com/power-system-analysis-and-designb-r-guptapower-system-analysis-and-designb-r-gupta-pdf-free.html>
3. Electric Power system –by Wiley
4. https://www.academia.edu/23758028/Electric_Power_Systems_Electric_Power_Systems
5. Essential Matlab for Engineers & Scientists-by Brian H. Hahn
6. https://faculty.ksu.edu.sa/sites/default/files/Essential+MATLAB+for+Engineers+and+Scientists+Fourth+Edition.pdf?fbclid=IwAR0KENPfdjdk3ky8nbYf0DFuPUu3p8_20mYLoD4l3DXReQ_gG2c2naYVWvk
7. 4. Advanced Microprocessor & Microcontrollers-by S.K.Venkata Ram
8. <https://www.amazon.com/Advanced-Microprocessors-Microcontrollers-Venkata-Ram/dp/8131806502>

AUTHOR DETAILS:

A. MD RAKIBUL HASAN



Masters of Science (M.Sc.), Department of Computer Science and Engineering, Islamic University, Bangladesh;
Bachelor of Science (B.Sc.), Department of Computer Science and Engineering, Prime University, Bangladesh;

He attained more than twenty diploma courses and a hundred certificate courses. His expertise and research interests include Artificial Intelligence, Artificial Neural Networks, Convolutional Neural Networks, Intelligent Transportation Systems, Information Technology, Computer Vision, Psychology, and Astronomy.

Email: rhp.rakibul7@gmail.com

ORCID: 0000-0003-4216-6626

Web of ScienceResearcherID: AAW-9863-2021

B. SAIKAT BARUA



Masters of Science (M.Sc.), Department of Computer Science and Engineering, Islamic University, Bangladesh;

Masters of Science (M.Sc.), Department of Applied Chemistry & Chemical Engineering, Islamic University, Bangladesh;

Bachelor of Science (B.Sc), Department of Electrical & Electronics Engineering, United International University, Dhaka , Bangladesh.

Email:saikat021112035@gmail.com