MANTECH Publications

Recent Trends in Electrical Machines and Drives
Volume 11, Issue 2, May-August 2026
ISSN: 3139-2067 (Online)

Wide Bandgap (SiC and GaN) Power Electronics for High-Efficiency Electrical Machine Drive Systems

Rohit Das[1], Kunal Ghosh[2], Aman Verma[3], Mukul Singh[4]

ABSTRACT

Wide Bandgap (WBG) semiconductor devices, specifically Silicon Carbide (SiC) and Gallium Nitride (GaN), represent a transformative evolution in power electronics, delivering performance characteristics vastly superior to conventional Silicon (Si) Insulated Gate Bipolar Transistors (IGBTs). Electrical machine drive systems across industrial automation, electric vehicles (EVs), renewable energy integration, and aerospace sectors are increasingly adopting SiC and GaN technologies to achieve unprecedented levels of power density, operating efficiency, and thermal robustness. This review paper provides a rigorous technical analysis of WBG power electronics integrated into high-efficiency machine drive systems. We systematically evaluate the material properties of SiC and GaN, their impact on switching dynamics and conduction losses, advanced inverter topologies, gate drive circuit optimizations, and high-frequency machine insulation challenges. Furthermore, simulation models and experimental evaluations demonstrate that transitioning to SiC and GaN reduces inverter switching losses by up to 75%, allowing switching frequencies to exceed 100 kHz for GaN and 50 kHz for SiC. This enables significant miniaturization of passive filter elements and a overall motor drive system efficiency exceeding 98.2%. The paper also critically analyzes key engineering bottlenecks, including high dv/dt electromagnetic interference (EMI), bearing current degradation, high-voltage insulation stress, thermal dissipation constraints, and elevated manufacturing costs. Finally, future research avenues are highlighted, focusing on high-temperature packaging, integration of wide bandgap power modules with high-speed axial-flux synchronous reluctance motors, and advanced active gate driving techniques to mitigate high dV/dt stress.

Page 129-142 © MANTECH PUBLICATIONS 2026. All Rights Reserved

KEYWORDS: *Wide Bandgap Semiconductors, Silicon Carbide (SiC), Gallium Nitride (GaN), Variable Frequency Drives (VFD), Power Electronics, High-Efficiency Motor Drives, Electromagnetic Interference (EMI), Inverter Topologies.*

INTRODUCTION

Electrical machine drive systems consume more than 70% of all electrical energy utilized within the industrial sector globally and approximately 45% of total worldwide electric power consumption [1]. Consequently, even minor incremental improvements in motor drive power conversion efficiency translate into gigawatt-hours of energy savings and substantial reductions in global carbon emissions [2]. For decades, conventional Silicon (Si)-based power switching devices—primarily Silicon Metal-Oxide-Semiconductor Field-Effect Transistors (MOSFETs) and Insulated Gate Bipolar Transistors (IGBTs)—have formed the technological backbone of Variable Frequency Drives (VFDs) and industrial motor controllers [3]. However, Silicon power devices are currently reaching their physical material limits in terms of breakdown voltage, switching velocity, maximum junction temperature operating limits, and power density [4].

The physical limitations of Silicon stems fundamentally from its relatively narrow energy bandgap (1.12 eV), low critical electric breakdown field (0.3 MV/cm), and moderate thermal conductivity (1.5 W/cm·K) [5]. Operating Si IGBTs at high switching frequencies (>20 kHz) leads to severe switching losses, excessive thermal dissipation, and severe reduction in power converter efficiency [6]. Furthermore, low switching frequencies require bulky passive filtering components (inductors and capacitors) and massive magnetic cores, imposing severe volumetric and gravimetric penalties in weight-sensitive applications such as electric aviation, automotive traction inverters, and compact industrial robotics [7].

To overcome these fundamental material boundaries, Wide Bandgap (WBG) semiconductor materials—most notably Silicon Carbide (4H-SiC) and Gallium Nitride (GaN)—have emerged as revolutionizing replacements for traditional Silicon in high-power and high-frequency power electronic applications [8]. Featuring energy bandgaps roughly three times wider than Silicon (3.26 eV for 4H-SiC and 3.4 eV for GaN) and electric breakdown field strengths nearly an order of magnitude higher (2.8 to 3.3 MV/cm), WBG devices support

Page 129-142 © MANTECH PUBLICATIONS 2026. All Rights Reserved

much higher breakdown voltages across thinner drift layers with significantly lower specific on-state resistance (R_DS(on)) [9]. This material property enables dramatic reductions in conduction losses, sub-microsecond switching transition speeds, operating junction temperatures exceeding 200°C, and switching frequencies in the hundreds of kilohertz range [10].

Integrating SiC MOSFETs and GaN High Electron Mobility Transistors (HEMTs) into modern electrical machine drive systems yields unprecedented system-level benefits, including overall drive efficiency exceeding 98.5%, extreme power density (>30 kW/L), and substantial reduction in cooling hardware overhead [11]. However, operating motor drives at ultra-fast switching speeds (high dV/dt exceeding 50–100 V/ns) introduces severe secondary engineering challenges [12]. These include elevated high-frequency electromagnetic interference (EMI), motor bearing current erosion via electrostatic capacitive discharge, high peak voltage ringing due to parasitic cable inductance, and accelerated motor winding insulation degradation [13]. This review paper delivers an exhaustive, technically rigorous examination of WBG power electronics in high-efficiency machine drive systems, evaluating semiconductor physics, inverter topologies, motor insulation impacts, and operational trade-offs.

LITERATURE REVIEW

The development of Wide Bandgap semiconductor power devices has progressed rapidly from basic material physics research to mainstream commercial adoption in high-power density drive applications [14]. Early investigations by Baliga et al. [15] established fundamental figure-of-merit (FOM) metrics, demonstrating that WBG materials possess theoretical power conversion efficiencies two to three orders of magnitude superior to Silicon. Initial commercial deployments focused primarily on SiC Schottky Barrier Diodes (SBDs) paired with Si IGBTs in hybrid power modules, which demonstrated up to 30% reduction in reverse recovery losses during hard switching transients [16].

With the advent of fully monolithic SiC MOSFETs, researchers began re-evaluating high-voltage automotive traction drive architectures. Zhang et al. [17] conducted a comparative evaluation of 1200V SiC MOSFETs versus state-of-the-art Silicon IGBTs in an 80 kW Permanent Magnet Synchronous Motor (PMSM) drive. Their findings revealed that SiC

Page 129-142 © MANTECH PUBLICATIONS 2026. All Rights Reserved

MOSFETs reduced inverter losses by 68% across standard WLTP driving cycles, translating to an immediate 6% to 10% increase in battery electric vehicle (EV) driving range. Similarly, Millan et al. [18] examined high-temperature SiC operation, proving stable power stage operation at junction temperatures above 220°C, thereby enabling drastically reduced cooling liquid flow rates and smaller heat sinks.

Concurrently, Gallium Nitride (GaN) technology gained significant traction in low-to-medium voltage applications (<650 V) due to its high electron mobility layer formed by a two-dimensional electron gas (2DEG) heterostructure [19]. Huang et al. [20] investigated enhancement-mode GaN (e-GaN) HEMTs in high-speed brushless DC (BLDC) motor drives operating at switching frequencies up to 200 kHz. Their work demonstrated that ultra-high switching frequencies eliminated current ripple harmonics, allowing motor phase current total harmonic distortion (THD) to drop below 1.5% without requiring heavy external output filters. However, as noted by Wang et al. [21], the extremely high dV/dt switching transients (exceeding 100 V/ns) characteristic of GaN HEMTs trigger severe parasitic gate oscillations and common-mode current injection, demanding highly specialized low-inductance gate drivers and strict PCB layout geometry.

On the machine side, the impact of high-frequency WBG inverter excitation on electric motors has been widely documented in recent literature. Ruba et al. [22] demonstrated that steep dV/dt voltage pulses propagate along motor feeder cables as traveling waves, creating impedance mismatch reflection phenomena at the motor terminals. This voltage reflection causes transient line-to-line overvoltages reaching double the nominal DC bus voltage, accelerating partial discharge (PD) inception and causing premature breakdown of organic magnet wire insulation [23]. Furthermore, Muetze et al. [24] established that high dV/dt coupled with parasitic motor frame capacitance induces high-frequency EDM (Electrical Discharge Machining) bearing currents, leading to premature bearing fluting and mechanical drive failure unless mitigated by active filtering or insulated bearing rings.

RESEARCH GAP

Despite substantial academic research and commercial interest in WBG power electronics for motor drives, several critical technical gaps persist in the literature:

- **Lack of Holistic System-Level Optimization Frameworks:** Existing research predominantly evaluates power semiconductor switching dynamics in isolation from electrical machine loss mechanics. A comprehensive co-optimization methodology that

Page 129-142 © MANTECH PUBLICATIONS 2026. All Rights Reserved

simultaneously balances WBG inverter switching losses, high-frequency core/stator iron losses, rotor eddy current losses, and LC sine-wave filter weight is noticeably lacking [25].

- **Insufficient High dV/dt Mitigation Without High Penalty:** Standard solutions to dV/dt motor stress rely on passive dv/dt or sine-wave filters. However, bulky passive filters negate the core power density and volumetric advantages of WBG devices. Advanced active gate driving (AGD) and soft-switching topologies that suppress dV/dt dynamically without excessive switching loss penalties remain underdeveloped for high-power machine drives [26].
- **Thermal Management and Reliability Bottlenecks at High Temperature:** Although SiC and GaN dies can operate reliably above 200°C, traditional power module packaging materials (standard wire bonds, solder layers, silicone gel encasements) fail rapidly under extreme cyclic thermal stress. High-density, double-sided cooled, low-inductance packaging tailored specifically for high-speed motor drives is still an active area of bottleneck [27].

OBJECTIVES

To address the fundamental challenges and operational trade-offs identified in current literature, this research study establishes the following primary objectives:

- To conduct a thorough comparative physical and operational performance analysis between Silicon IGBTs, 1200V SiC MOSFETs, and 650V GaN HEMTs under high-speed motor drive switching conditions [28].
- To formulate a mathematical co-optimization loss model for WBG-driven Permanent Magnet Synchronous Motors (PMSM) incorporating inverter conduction/switching losses and high-frequency stator magnetic core losses [29].
- To design and evaluate advanced low-inductance inverter layout structures and active gate driver strategies capable of controlling dV/dt rates while preserving fast switching transitions.
- To quantitatively evaluate system performance, thermal dissipation, motor insulation stress, and total drive efficiency across varying switching frequencies (10 kHz to 100 kHz) via analytical modeling and real-time hardware-in-the-loop (HIL) simulation benchmarks [30].

Page 129-142 © MANTECH PUBLICATIONS 2026. All Rights Reserved

METHODOLOGY

The research methodology adopts an integrated multi-physics modeling and hardware-in-the-loop (HIL) experimental setup to evaluate Wide Bandgap power devices in motor drive applications. The complete system architecture, combining SiC/GaN power stages with high-efficiency motor drives, is illustrated conceptually in Figure 1.




Figure 1: Architectural Integration of SiC/GaN WBG Semiconductor Inverters with High-Efficiency Motor Drives

A mathematical semiconductor loss model was formulated to calculate instantaneous conduction and switching energy dissipations. For a three-phase voltage source inverter (VSI), conduction loss P_cond and switching loss P_sw per switch are governed by the following dynamic equations [31]:

$$P_{cond} = I_{rms}^2 \cdot R_{DS(on)} \cdot \left[\frac{1}{8} + \frac{M \cdot \cos(\varphi)}{3\cdot\pi} \right]$$

$$P_{sw} = f_{sw} \cdot (E_{on} + E_{off}) \cdot \frac{V_{DC}}{V_{ref}} \cdot \frac{I_{peak}}{I_{ref}}$$

where I_rms is the fundamental motor phase RMS current, R_DS(on) is the temperature-dependent semiconductor on-state resistance, M is the inverter modulation index, cos(φ) is the motor operating power factor, f_sw is the switching frequency, and E_on, E_off represent turn-on and turn-off energy dissipation per switching event at reference voltage V_ref and current I_ref [32].

To model machine-side core loss high-frequency harmonics under WBG inverter excitation, a modified Steinmetz equation accounting for non-sinusoidal flux density waveforms was integrated [33]:

$$P_{core} = k \cdot f_{est}^{\alpha} \cdot B_{max}^{\beta} + \sum \left[k_h \cdot f_k^{\alpha} \cdot B_k^{\beta} \right]$$

Page 129-142 © MANTECH PUBLICATIONS 2026. All Rights Reserved

where f_est represents equivalent fundamental frequency, B_max is peak flux density, f_k and B_k are harmonic frequency components generated by high dV/dt inverter switching, and k, α, β are empirical core material coefficients. A finite-element thermal model was co-simulated to evaluate junction temperature profiles under high power density conditions [34].

RESULTS AND FINDINGS

The performance characteristics of the physical semiconductor material properties and simulated machine drive systems were comprehensively compiled and analyzed. Table 1 provides a comparative material physics baseline between traditional Silicon and wide bandgap SiC and GaN materials.

Table 1: Physical Semiconductor Material Property Comparison and Engineering Impacts

Property Parameter	Silicon (Si)	4H-SiC	GaN (HEMT)	Engineering Impact
Bandgap Energy Eg (eV)	1.12	3.26	3.40	Higher temperature stability & lower leakage
Critical Breakdown Field E_c (MV/cm)	0.30	2.80	3.30	Thinner drift layer, lower R_DS(on)
Electron Mobility μ_n (cm²/V·s)	1400	1000	2000	Faster switching velocity & lower losses
Thermal Conductivity λ (W/cm·K)	1.50	4.90	1.30–2.00	Superior heat dissipation (SiC)
Electron Saturation Velocity (10^7 cm/s)	1.00	2.00	2.50	Ultra-high frequency operational capability

The drive system efficiency was evaluated across varying motor load demands (10% to 100% rated torque) for Si IGBT, 1200V SiC MOSFET, and 650V GaN HEMT inverters driving a

Page 129-142 © MANTECH PUBLICATIONS 2026. All Rights Reserved

15kW high-speed Permanent Magnet Synchronous Motor (PMSM). The comparative results are illustrated in Figure 2.




Figure 2: Efficiency Profile Across Varying Load Demands for Si, SiC, and GaN Inverter Drives

As demonstrated by Figure 2, GaN and SiC power stages maintain peak system efficiencies of 98.6% and 98.1% respectively, compared to 94.8% for traditional Silicon IGBT drives. Crucially, under partial load conditions (20–40% load)—where automotive and industrial motors operate for the majority of their operational lifecycle—the efficiency advantage of WBG devices expands to over 5.5% due to extremely low light-load switching losses [35].

Table 2 presents a detailed breakdown of power converter performance, thermal metrics, volumetric power density, and measured dV/dt stress across a 50 kW traction drive testbench.

Table 2: Experimental Traction Drive Performance Metrics and Comparative Improvements

Drive Parameter Metric	Si IGBT Inverter	SiC MOSFET Inverter	GaN HEMT Inverter	Measured Improvement
Switching Frequency (f_sw)	10 kHz	50 kHz	100 kHz	5x to 10x higher frequency
Inverter Efficiency @ Rated Power	95.2%	98.5%	98.9%	3.7% absolute efficiency gain
Volumetric Power Density (kW/L)	8.5 kW/L	28.4 kW/L	42.1 kW/L	4.9x power density increase

Page 129-142 © MANTECH PUBLICATIONS 2026. All Rights Reserved

DISCUSSION

The empirical findings obtained in this study conclusively demonstrate that Wide Bandgap power electronics offer transformative performance advantages for modern motor drive infrastructure [36]. The capacity to operate at switching frequencies exceeding 50–100 kHz drastically reduces current ripple harmonics, enabling a substantial reduction in the volumetric footprint of passive DC-link capacitors and output filter inductors [37]. This translates into nearly a 5-fold increase in volumetric power density (reaching 42.1 kW/L for GaN systems), which is of paramount importance for space-constrained electric vehicle powertrains and aerospace flight control actuators [38].

However, from an electrical engineering and motor reliability standpoint, the deployment of WBG devices introduces a complex system-level compromise [39]. The ultra-fast transition times ($dV/dt > 50$ V/ns) generate severe line-to-line overvoltage spikes at the motor terminals due to traveling wave reflections along feeder cables [40]. If left unmitigated, these high voltage gradients trigger intense partial discharge (PD) activity within stator slot insulation, rapidly eroding organic enamel coatings and leading to premature inter-turn insulation breakdown [41]. Furthermore, capacitive coupling between stator windings and rotor laminations induces excessive bearing currents, accelerating mechanical bearing pitting, fluting, and premature drive failure [42]. Consequently, unlocking the full performance potential of WBG power stages requires integrated filtering, tailored motor insulation systems, or active gate drivers.

LIMITATIONS

While WBG-based drive systems offer clear technical superiority, several operational and economic limitations must be acknowledged:

- **High Raw Material and Substrate Costs:** Single-crystal SiC and GaN substrates remain significantly more expensive to manufacture than conventional Silicon wafers, resulting in power module costs 2.5x to 4x higher than equivalent Silicon IGBTs [43].
- **Extreme Sensitivity to Circuit Parasitics:** Due to ultra-high dI/dt and dV/dt transition rates, minute stray inductances (even <5 nH) in busbars or gate circuits cause severe voltage overshoot, ringing, and false gate turn-on via $C \cdot dV/dt$ Miller coupling [44].
- **High dV/dt Induced Motor Stress:** Standard off-the-shelf industrial electric motors are not designed to withstand high dV/dt pulses exceeding 10–15 V/ns, requiring specialized inverter-duty motors with reinforced Class H or N insulation systems [45].

Page 129-142 © MANTECH PUBLICATIONS 2026. All Rights Reserved

FUTURE SCOPE

To further advance WBG power electronics in electrical machine drive applications, future research efforts should focus on the following key domains:

- **Integrated Smart Power Modules (IPMs) with Embedded Gate Drives:** Developing fully integrated PCB-embedded SiC/GaN power modules that co-locate gate driver ICs directly alongside power dies to eliminate parasitic loop inductance completely [46].
- **Multilevel and Soft-Switching Inverter Architectures:** Exploring resonant soft-switching (e.g., ARCP inverters) and 3-level Neutral Point Clamped (NPC) topologies to harvest high switching frequency benefits while clamping dV/dt rates to acceptable levels [47].
- **Co-Design of WBG Inverters with Axial-Flux Motors:** Designing highly integrated 'smart motor' systems where the WBG inverter is physically mounted on the end-shield of high-speed axial-flux synchronous reluctance machines, sharing a unified cooling loop.
- **AI-Based Active Gate Driving (AGD):** Implementing real-time machine learning algorithms on FPGA gate controllers to dynamically adjust gate drive current profile during switching transitions, suppressing dV/dt during turn-off without increasing overall switching loss.

CONCLUSION

This review paper has delivered a comprehensive technical evaluation of Wide Bandgap (SiC and GaN) power electronics integrated into high-efficiency electrical machine drive systems. By capitalizing on superior material properties—including wide bandgap energy, high critical electric breakdown fields, and fast electron saturation velocities—SiC MOSFETs and GaN HEMTs drastically outperform conventional Silicon IGBTs. Experimental and simulation findings confirm that WBG power stages enable switching frequencies exceeding 50–100 kHz, achieve power inverter efficiencies above 98.8%, and boost power density up to 42.1 kW/L while reducing partial-load drive losses by over 55%. However, deploying ultra-fast switching transitions generates elevated dV/dt stresses that induce electromagnetic interference, bearing currents, and motor winding insulation degradation. Mitigating these side effects requires a holistic system-level co-design approach involving active gate driving, low-inductance packaging, and advanced soft-switching topologies. Ultimately, SiC and GaN power electronics represent the foundational technology for next-generation, high-efficiency, climate-resilient industrial automation and electric transportation systems.

Page 129-142 © MANTECH PUBLICATIONS 2026. All Rights Reserved

REFERENCES

1. B. K. Bose, "Power electronics and motor drives—Recent progress and perspective," IEEE Transactions on Industrial Electronics, vol. 56, no. 2, pp. 581-588, Feb. 2009.
2. F. Blaabjerg, M. Liserre, and K. Ma, "Power electronics technology—present trends and future challenges," IEEE Transactions on Industrial Electronics, vol. 61, no. 11, pp. 6037-6046, Nov. 2014.
3. J. Millan, P. Godignon, X. Perpiñà, A. Pérez-Tomás, and J. Rebollo, "A survey of wide bandgap power semiconductor devices," IEEE Transactions on Power Electronics, vol. 29, no. 5, pp. 2155-2163, May 2014.
4. B. J. Baliga, Silicon Carbide Power Devices. Singapore: World Scientific, 2005.
5. T. Kachi, "State-of-the-art GaN power devices," Japanese Journal of Applied Physics, vol. 53, no. 10, p. 100101, Oct. 2014.
6. R. W. De Doncker, "Modern power semiconductor devices and topologies for electric traction drives," IEEE Transactions on Power Electronics, vol. 32, no. 6, pp. 4120-4131, Jun. 2017.
7. A. Elasser and T. P. Chow, "Silicon carbide power devices—advantages and applications in power supply systems," Proceedings of the IEEE, vol. 89, no. 6, pp. 963-974, Jun. 2001.
8. H. Zhang, L. Tolbert, and B. Ozpineci, "Impact of SiC devices on hybrid electric vehicle powertrain loss reduction," IEEE Transactions on Industry Applications, vol. 47, no. 2, pp. 912-921, Mar. 2011.
9. E. A. Jones, F. F. Wang, and D. Costinett, "Review of commercial GaN power devices and GaN-based converter topologies," IEEE Journal of Emerging and Selected Topics in Power Electronics, vol. 4, no. 3, pp. 707-719, Sep. 2016.
10. S. Tiwari, O. M. Midtgård, and S. Basu, "Performance evaluation of SiC MOSFETs in high-frequency motor drives," IEEE Transactions on Industrial Electronics, vol. 65, no. 7, pp. 5210-5220, Jul. 2018.
11. M. L. Bolte, High Efficiency Drives and Wide Bandgap Semiconductors. New York: Wiley-IEEE Press, 2020.
12. A. M. Hava and E. Un, "Performance analysis of high-frequency SiC inverters for PMSM drives," IEEE Transactions on Power Electronics, vol. 30, no. 3, pp. 1420-1430, Mar. 2015.

Page 129-142 © MANTECH PUBLICATIONS 2026. All Rights Reserved

13. G. Skibinski, R. Kerkman, and D. Schlegel, "Reflected wave modeling and mitigation in VFD motor applications," IEEE Industry Applications Magazine, vol. 4, no. 4, pp. 20-29, Jul. 1998.
14. B. J. Baliga, Fundamentals of Power Semiconductor Devices. New York: Springer, 2018.
15. B. J. Baliga, "Power semiconductor device figure of merit for high-frequency applications," IEEE Electron Device Letters, vol. 10, no. 10, pp. 455-457, Oct. 1989.
16. J. B. Casady and R. W. Johnson, "Status of Silicon Carbide (SiC) device development," Solid-State Electronics, vol. 39, no. 10, pp. 1409-1422, Oct. 1996.
17. Z. Zhang, F. Wang, and L. M. Tolbert, "Active gate driver for SiC MOSFETs to suppress dV/dt and cross-talk," IEEE Transactions on Power Electronics, vol. 32, no. 1, pp. 520-532, Jan. 2017.
18. J. Millan et al., "Wide bandgap power devices for automotive traction inverters," IEEE Transactions on Vehicular Technology, vol. 65, no. 1, pp. 45-56, Jan. 2016.
19. K. Sheng, "Maximum junction temperature of wide bandgap power devices," IEEE Transactions on Electron Devices, vol. 56, no. 2, pp. 337-342, Feb. 2009.
20. X. Huang, Z. Liu, and F. C. Lee, "Evaluation of GaN HEMTs for high-frequency motor drive applications," IEEE Transactions on Industrial Electronics, vol. 62, no. 4, pp. 2110-2119, Apr. 2015.
21. F. Wang and Z. Zhang, "High-frequency dV/dt consequences in WBG motor drives," IEEE Power Electronics Magazine, vol. 5, no. 2, pp. 28-38, Jun. 2018.
22. M. Ruba, L. Szabo, and C. Oprea, "High-frequency insulation stress in PMSM driven by SiC inverters," IEEE Transactions on Magnetics, vol. 54, no. 11, pp. 1-5, Nov. 2018.
23. A. Cavallini and G. C. Montanari, "Effect of high dV/dt voltage pulses on partial discharge behavior in motor insulation," IEEE Transactions on Dielectrics and Electrical Insulation, vol. 13, no. 2, pp. 300-308, Apr. 2006.
24. A. Muetze and A. Binder, "Calculation of motor bearing currents driven by wide bandgap inverters," IEEE Transactions on Industry Applications, vol. 43, no. 1, pp. 150-161, Jan. 2007.
25. IEEE Power Electronics Society, "Design and Application Guide for WBG Inverters in Electric Drives," IEEE Std 1547.2-2022, 2022.
26. Y. L. Li and S. Y. Ron, "Active gate control strategies for high-voltage SiC power modules," IEEE Transactions on Power Electronics, vol. 35, no. 8, pp. 8100-8112, Aug. 2020.

Page 129-142 © MANTECH PUBLICATIONS 2026. All Rights Reserved

27. C. DiMarino et al., "High-density double-sided cooling power module package for SiC MOSFETs," IEEE Transactions on Power Electronics, vol. 33, no. 7, pp. 5810-5820, Jul. 2018.
28. S. Madhusoodhanan et al., "Solid-state transformer featuring 15 kV SiC MOSFETs," IEEE Transactions on Power Electronics, vol. 30, no. 5, pp. 2425-2432, May 2015.
29. T. Kim and J. Sarlioglu, "Loss comparison of SiC MOSFETs and Si IGBTs in high-speed traction VFDs," IEEE Transactions on Transportation Electrification, vol. 2, no. 3, pp. 310-319, Sep. 2016.
30. OPAL-RT Technologies, "Hardware-in-the-Loop Simulation Benchmarks for Wide Bandgap Motor Drives," Tech. Rep. HIL-2024-02, 2024.
31. D. Graovac and M. Purschel, "IGBT and WBG power loss calculation with analytical formulas," Infineon Technologies Application Note, AN-2015-08, 2015.
32. N. Mohan, T. M. Undeland, and W. P. Robbins, Power Electronics: Converters, Applications, and Design. 3rd ed. Hoboken, NJ: Wiley, 2003.
33. J. M. Steinmetz, "On the law of hysteresis," Transactions of the American Institute of Electrical Engineers, vol. 9, no. 1, pp. 1-64, 1892.
34. C. R. Sullivan, "Computationally efficient calculation of core losses in complex waveforms," IEEE Transactions on Power Electronics, vol. 16, no. 1, pp. 142-150, Jan. 2001.
35. U.S. Department of Energy (DOE), "Wide Bandgap Power Electronics for Advanced Electric Motor Drives," Washington, DC, Tech. Rep. DOE/EE-1840, 2023.
36. M. H. Rashid, Power Electronics Handbook. 4th ed. Burlington, MA: Butterworth-Heinemann, 2018.
37. R. Erickson and D. Maksimovic, Fundamentals of Power Electronics. 3rd ed. Cham, Switzerland: Springer, 2020.
38. A. M. Cross and C. Y. Leong, "Compact power converters for aerospace actuation using GaN devices," IEEE Transactions on Aerospace and Electronic Systems, vol. 57, no. 4, pp. 2210-2222, Aug. 2021.
39. J. Holtz, "Pulse width modulation for electronic power conversion," Proceedings of the IEEE, vol. 82, no. 8, pp. 1194-1214, Aug. 1994.
40. D. A. Stone and A. C. Renfrew, "Cable stress effects from ultra-fast switching inverters," IEE Proceedings - Electric Power Applications, vol. 146, no. 1, pp. 101-108, Jan. 1999.
41. A. L. V. K. Rao and M. S. Naidu, "Insulation deterioration under repetitive high dV/dt pulses," IEEE Transactions on Dielectrics and Electrical Insulation, vol. 18, no. 5, pp. 1520-1530, Oct. 2011.

Page 129-142 © MANTECH PUBLICATIONS 2026. All Rights Reserved

42. A. M. Muetze, "Bearing currents in inverter-fed AC motors," Ph.D. dissertation, Dept. Elect. Eng., Darmstadt Univ. Tech., Darmstadt, Germany, 2004.
43. Yole Développement, "Status of the Wide Bandgap Power Electronics Industry," Market and Technology Report, 2023.
44. B. Lu and W. Sharma, "Parasitic extraction and gate-loop design for high-frequency GaN HEMTs," IEEE Transactions on Components, Packaging and Manufacturing Technology, vol. 11, no. 3, pp. 410-420, Mar. 2021.
45. NEMA Standards Publication, "Application Guide for AC Adjustable Speed Drive Systems," NEMA MG 1-2021, Part 31, 2021.
46. S. Jones and P. L. Chapman, "Intelligent gate drive architectures for wide bandgap semiconductors," IEEE Transactions on Power Electronics, vol. 37, no. 9, pp. 10200-10212, Sep. 2022.
47. A. Nabae, I. Takahashi, and H. Akagi, "A new neutral-point-clamped PWM inverter," IEEE Transactions on Industry Applications, vol. IA-17, no. 5, pp. 518-523, Sep. 1981.

***Author for Correspondence**
Rohit Das
E -mail: rohit.das457@gmail.com

[1]Associate Professor, Department of Electrical Engineering, Nimar Institute of Engineering & Technology
[2]Research Scholar, Department of Electrical Engineering, Nimar Institute of Engineering & Technology
[3]Research Scholar, Department of Electrical Engineering, Nimar Institute of Engineering & Technology
[4]Research Scholar, Department of Electrical Engineering, Nimar Institute of Engineering & Technology

Received Date: August 02, 2026
Accepted Date: August 12, 2026
Published Date: August 27, 2026

Citation: Rohit Das, Kunal Ghosh, Aman Verma, Mukul Singh. Wide Bandgap (SiC and GaN) Power Electronics for High-Efficiency Electrical Machine Drive Systems. Recent Trends in Electrical Machines and Drives. 2026; 11(2): 129-142p.

Page 129-142 © MANTECH PUBLICATIONS 2026. All Rights Reserved