

# ***An Examination of Switchgear Analysis and the Most Frequently Encountered Obstacles in Switchgear***

**Shiva Prasad H<sup>1</sup>, Rishab Ahuja<sup>2</sup>**

Associate Professor<sup>1</sup>, Student<sup>2</sup>

Department of EEE

Dayananda Sagar College of Engineering, Bengaluru,

**Corresponding Author's Email:** - ahujarishab888@gmail.com<sup>2</sup>

## ***Abstract***

*With the adoption of new sensor technologies and the expansion of IoT devices, the digitalization of produced goods has now become a phenomena. People who own massive, expensive machinery would like to maintain track of the important characteristics of their assets. As a result, medium voltage equipment, particularly switchgear diagnostics, has grown in value. With varied degrees of tolerance and operating efficiency, on-site studies and monitoring of circuit breaker drives, contacts, gas quality, gas density, and partial discharges might be accomplished. They are installed at substations to provide energy to cities via electrical networks such as overhead power lines and subterranean cables. Because of the high voltage and current flow, safety and efficiency are key problems with this equipment. As a result, numerous types of sensors are utilised in the system to monitor its operation. This article gives a comprehensive assessment of the Switchgear Study, its implementations, and the issues found.*

**Keywords:** *Medium Voltage Switchgears, Gas Insulated Switchgear, IoT, Safety methods, Operational Efficiency, System Performance.*

## **INTRODUCTION**

Switchgear was invented before electricity. The initial prototypes were relatively simple, with all parts affixed directly to a

wall. They were then mounted in wooden frames. For fire safety reasons, the wood was replaced with slate or marble. Because the switching and measuring devices could

be attached to the front while the wire was on the back, additional changes were made. A tumbler switch with an ordinary fuse is the most basic sort of switchgear, and it was used to operate and secure lights and other equipment in homes, offices, and other locations. To regulate and safeguard higher-rated circuits, a high-rupturing capacity (H.R.C.) fuse and a switch can be utilised. Furthermore, in a high-voltage grid, such switchgear is unprofitable. Electrical disconnect switches, fuses, and circuit breakers comprise switchgear, which is used to operate, secure, and separate electrical equipment in an electric power system. Switchgear is used to de-energize machinery in order to perform maintenance on it and to remove problems downstream[1]. This sort of equipment is closely related to the efficiency of the power supply. Arc energy may be safely stored and handled with oil-filled switchgear. By the early twentieth century, it was nearly certain that a switchgear lineup would consist of a metal-enclosed structure with electrically controlled switching components and oil circuit breakers. Today, air-blast, vacuum, or SF6 equipment has effectively replaced oil-filled equipment, allowing automated equipment to safely handle a wide range of currents and input voltages. Control

components that conduct or disrupt the flow of electrical power, such as switches, circuit breakers, fuses, and lightning, and control systems for monitoring, controlling, and safeguarding power driving elements, such as control panels, current transformers, future transformers, protection relays, and related circuits, comprise a switchgear assembly. One of the most fundamental elements of switchgear is security, which is the interruption of short-circuiting and overload fault currents while maintaining operation on unaffected circuits Gts. Switchgear also provides circuit isolation from power supply. Switchgear can also increase system availability by allowing many sources to supply a load at the same time. Gas-insulated switchgear takes up less space than air-insulated equipment, although it is more expensive. The gas-insulated switchgear is an effective, but more expensive, kind of switchgear. Gas-insulated switchgear takes up less space than air-insulated switchgear, but the equipment is more expensive. Pressurized sulphur hexafluoride gas (SF6) is used to insulate conductors and contacts in switchgear (GIS)[2]. The combination of components in the switchgear enclosure allows them to interrupt fault currents of thousands of volts. A circuit breaker is the key component that interrupts fault

currents (located inside a switchgear enclosure). The arc must be quenched with caution when the circuit breaker splits apart the contacts (disconnects the circuit). Gas (SF<sub>6</sub>) circuit breakers employ a magnetic field to lengthen the arc and then focus on the dielectric power of the SF<sub>6</sub> gas to quench the extended arc. Because there is little to ionise other than the contact material in vacuum interrupter circuit breakers, the arc quenches as it is extended by a little distance (approximately 2-8 mm)[3]. Because the arc isn't hot enough to maintain a plasma at zero current, the current ceases, and the vacuum can endure the voltage spike. Vacuum circuit breakers are extensively used in current medium-voltage switchgear up to 40,500 volts. Vacuum circuit breakers are inappropriate for breaking high DC voltages because there is no "current zero" period for DC. By beginning to gasify the contact material, the plasma arc may be fed on its own[4]. Because of its good isolation and thermal qualities, SF<sub>6</sub> is now often used as the insulation and break-down medium in medium voltage GIS. While SF<sub>6</sub> has many advantages, it is also the world's most harmful greenhouse gas. Only SF<sub>6</sub> pollution contributed 0.5% of global warming per year. Because of SF<sub>6</sub>'s severe

greenhouse effects, a different approach to SF<sub>6</sub> in switchgear is necessary. [5]

## **TYPES OF SWITCHGEAR**

The switchgear is available in three different types: LV (Low Voltage), MV (Medium Voltage), and HV (High Voltage).

### **Low Voltage Switchgear**

A power grid that runs at less than 1 kV is referred to as low voltage switchgear. The power distribution transformer's secondary (low-tension) side also includes low-voltage switchgear. A substation is an assembly of transformers and switchgear. Low-voltage switchgear is typically used to supply LV-MCCs and low-voltage switchboards, as well as various branch and feeder systems. It provides energy and process power to key energy and process applications such as heavy industry, construction, mining and steel, petrochemical, pulp and paper, water, datacenters, and healthcare. Switches, LV circuit breakers, HRC fuses, earth leakage (EL), disruptive circuit breakers, unloading electrical insulators, MCBs, and MCCBs are among the most popular pieces of equipment. [6]

### **Medium Voltage Switchgear**

A medium voltage switchgear device can handle voltages ranging from 3 to 36 kV. There are several kinds available, including metal-enclosed outdoor type, metal-enclosed interior type, and outdoor type without metal enclosure. In this type of switchgear, vacuum, SF<sub>6</sub>, and oil can all be employed as disturbance media. This type of power network's principal duty is to interrupt current flow in the case of a grid breakdown. This is utilised in a number of applications and is capable of ON/OFF service, short circuit current interference, capacitive current switching, and inductive current switching. Examples of uses include arc furnaces, medium-voltage electrical transmission lines, SF<sub>6</sub> gas-insulated, air magnetic, gas-insulated, vacuum, and electrical power producing stations [7].

### **High Voltage Switchgear**

A power system that works with voltages more than 36 kV is known as high voltage switchgear. Because of the high voltage level, the arcing caused during switching operation is likewise quite high. As a result, greater care should be used while constructing high-voltage switchgear. Because the high voltage circuit breaker (CB) is the most critical component of HV switchgear, it must include particular

qualities to ensure safe and reliable functioning. It is extremely improbable that high-voltage circuits would have defective tripping and switching operations. caused by friction in the dielectric contact inside the circuit breaker, which may result in the destruction of the entire system or workplace in the worst case scenario, this light or sparks will be sensed by the light sensor and will activate an alarm informing the controller about the malfunction occurring, thus avoiding any damage to the system. In the event of an emergency, the system may be totally shut down, allowing the industry to keep a better and more consistent check[8].

### **CIRCUIT BREAKER**

A circuit breaker is the key component that interrupts fault currents (within a switchgear enclosure). Because the arc is quenched when the circuit breaker separates the contacts (disconnects the circuit), careful design is required. Circuit breakers and fuses trip when current reaches a preset safe level. Other crucial flaws, such as imbalanced currents—for example, where a transformer winding comes into contact with the ground—are undetectable. Circuit breakers and fuses cannot distinguish between short circuits and high levels of electrical demand on their own [9].

## **TYPES OF CIRCUIT BREAKER**

Circuit breakers/insulated Switchgears fall into these five types: Oil circuit breaker, Air brake circuit breaker, Air blast circuit breaker, GIS / Sulfur hexafluoride circuit breaker, Hybrid circuit breaker, Vacuum circuit breaker.

### **Oil Insulted Circuit Breaker**

To blast a jet of oil down the direction of the arc, oil circuit breakers depend on the vaporization of some of the oil. Arcing causes hydrogen gas to be emitted as a vapor. Mineral oil is a more effective insulator than air. As current carrying contacts in the oil separate, the arc in the circuit breaker is initiated at the time of contact separation, and the oil is vaporized and decomposed into largely hydrogen gas, thereby forming a hydrogen bubble around the electric arc. Since the current crosses zero crossings of the cycle, this intensely dense gas bubble around the arc stops the arc from re-striking.[10]

### **Air Insulted Circuit Breaker**

Air Insulated Circuit Breaker (ACB) is an electrical device used to provide Overcurrent and short-circuit protection for electric circuits over 800 Amps to 10K Amps. To extend the arc, air circuit breakers may use compressed air (puff) or the magnetic power of the arc itself. The

elongated arc would ultimately exhaust itself because the duration of the sustainable arc is determined by the available voltage. Alternatively, the contacts are quickly swung into a shallow enclosed chamber, blowing out the arc as the expelled air escapes [10].

### **Gas Insulated / SF6 Circuit Breaker**

Sulfur hexafluoride (SF6) is used as an insulator in gas-insulated switchgear (GIS). It is a more costly but more efficient form of switchgear. To insulate the conductors and contacts, pressurised SF6 is employed. The combination of components in the GIS switchgear enclosure allows them to interrupt fault currents of thousands of amps.

### **Hybrid Circuit Breaker**

In hybrid switchgear, components of traditional air-insulated switchgear (AIS) and SF6 gas-insulated switchgear (GIS) technology are blended. Its architecture is lightweight and modular, combining numerous different functions into a single module [10].

### **Vacuum Insulated Circuit Breaker**

Since there is little to ionize other than the contact medium in circuit breakers with vacuum interrupters, the arc quenches as it is extended by a tiny distance (about 2–8

mm). The arc isn't hot enough to hold a plasma at zero current, so current bridges the gap, and can then endure the voltage spike. Current medium-voltage switchgear up to 40,500 volts commonly uses vacuum circuit breakers. They are fundamentally unsuitable for interrupting DC faults, unlike the other styles. Since there is no 'current zero' cycle for DC, vacuum circuit breakers are unsuitable for breaking high DC voltages. The plasma arc will self-feed by condensing. By continuing to gasify the contact material, the plasma arc will self-feed[10].

#### **APPLICATIONS OF SWITCHGEAR**

Power stations employed simple disconnectors, often known as open knife switches, to separate or de-energize equipment. Manually opening such disconnectors proved hazardous when power levels rose, forcing the adoption of geared switches, which were subsequently combined to produce "Switchgear." It aids in the protection of appliances and electrical machinery. The switch in our home is used to manually open and stop the electrical circuit, whereas the electrical fuse protects the circuit from overcurrent and short circuit failures. Any electrical circuit, including high-voltage electrical control systems, requires switching and safety devices. This switching and

defensive method becomes more complex in high voltage and extra-high voltage systems in order to safely and securely interrupt high fault currents. Furthermore, from a business aspect, any electrical power supply needs a weighing, controlling, and regulating scheme. Switchgear and power system safety relate to the overall system. Safety of switchgear is crucial in today's power networks, from generation to transmission to distribution. Regular load currents, as well as basic faults in the control grid, must be carried, made, and split by the switchgear in the same way that a switch does. It is also capable of measuring and managing the various characteristics of electrical power systems. To protect electrical systems, switchgear includes circuit breakers, current transformers, voltage transformers, safety relays, measuring devices, electrical switches, electrical fuses, miniature circuit breakers, lightning arresters or surge arresters, electrical isolators, and other related equipment. Electric switchgear is required at any switching point in the electrical power system. There are varied voltage levels and hence fault levels between producing stations and load centres. As a result, several types of switchgear assembly are required depending on the voltage levels in the system. To ensure safety in all domains,

electrical switchgear is utilised in industrial activities, industrial projects, home and commercial structures, as well as power grid networks.

## **CHALLENGES OBSERVED IN SWITCHGEAR**

Even though switchgear serves as a barrier between various electrical equipment, it must be regularly maintained to avoid breakdowns. Increased heat, increased pressure, and arc faults are the most prevalent problems seen in switchgears.

### **Temperature Rise**

Temperature has become a big worry due to the extremely high voltage equipment contained within the switchgear. With numerous trips to the setup, it is hard to continually watch the switchgear temperature conditions since the faults that have occurred might deteriorate if not treated immediately [11].

### **Vacuum/Over Pressure**

A small amount of pressure persists or escapes from within the switchgear containers during the suction of air, resulting in a significant decrease in switchgear performance. This could have an impact on future processes or may result in an explosion due to the

accumulation of pressure in the undesired breach inside the system [12].

### **Arc Flash/Arching**

During the opening of current-carrying contacts in a circuit breaker, the medium between the opening contacts gets strongly ionised, allowing the interrupting current to travel via a low resistance channel even after the contacts are physically disconnected. An arc fault in switchgear causes a long-term power loss, equipment damage, and a safety risk to employees; this compels us to take preparations ahead of time to avoid any undesirable mishaps. Continuous equipment monitoring and early identification of probable failures can aid in the development of a more proactive and complete arc-flash prevention system [13].

## **CONCLUSION**

The major goal of this review is to provide information on switchgear and the problems that have been encountered. Electrical switchgear is a crucial component of electrical control systems across the world, and it is used to transmit as well as selectively separate electrical loads. The sudden temperature spike at a specific region, in example, might indicate corrosion or another form of damage. Thermal effects are particularly noticeable

in medium voltage switchgear used in distribution networks, where electrical currents can reach tens of thousands of amperes. As a result, keeping switchgear in excellent operating order during its lengthy life becomes critical. Currently, switchgear bus temperature monitoring is done on a regular basis either by human inspections with IR cameras or through pricey fibre optic systems[14]. The aim to enhance the electrical system's maintenance plan is one of the important results of the online monitoring and diagnostic technique. As a result, in order to execute condition-based maintenance for medium voltage (MV) switchgear and breakers, a new modular solution for online condition monitoring needs be devised. [15]. Using specific sensor technologies, the solution can identify probable faults and plan maintenance ahead of time. Circuit breaker failure modes should be estimated, including open and close command malfunction, charging mechanism malfunction, current interruption difficulties (contact wear), overheating, and the overall health index of the monitored equipment. The arc flash danger is connected to workplace electrical safety and has garnered a lot of attention as part of the safety programme for many installations[16]. An effective technique to reducing arc flash dangers in current

industrial and commercial buildings is a critical goal. Electrical equipment failure is frequently followed by anomalous temperature changes[17]. As a result, temperature monitoring of power equipment is the most effective and cost-efficient method of power equipment safety monitoring, which is critical to the safe functioning of power equipment. This leads us to managing the net-pressure inside the switchgear to avoid any overpressure that could lead to serious hazards; thus, this should be maintained using affordable developed technologies that allow us to constantly monitor the system health of the switchgear and its components using online monitoring systems.

## REFERENCES

1. K. Matsushita, Y. Matsuura, T. Funabashi, N. Takeuchi, T. Kai and M. Oobe, "Study for the performance of high speed switchgear for protection of in-house generation system," Proceedings of 1996 IAS Industrial and Commercial Power Systems Technical Conference, New Orleans, LA, USA, 1996, pp. 91-95, doi: 10.1109/ICPS.1996.533941.

2. Bolin, Phil & Koch, Hermann. (2008). Gas insulated substation GIS.13. 10.1109/TDC.2008.4517307. in electrical room. CIRED - Open Access Proceedings Journal. 2017. 198-201. 10.1049/oap-cired.2017.0385.
3. Saurabh Saxena Maroof Ali Alok Singh Kapil Gandhi, &ldquo;Various Types of Circuit Breakers used in Power System for Smooth Working of the Transmission Line,&rdquo; MIT International Journal of Electrical and Instrumentation Engineering, Vol. 2, No. 2, Aug. 2012, pp. (106-111) [4] S. Tokoyoda, T. Inagaki, K. Tahata, F. Page, K. Kamei, T. Minagawa
4. IEEE Transactions on components, packaging and manufacturing technology —PART A, VOL. 21, NO. 1, MARCH 1998 33 “Arc Motion and Pressure Formation in Low Voltage Switchgear” ,Manfred Lindmayer and Joachim Paulke.
5. Preve, Christophe & Lahaye, Gérard & Richaud, Myriam & Maladen, Romain & Penelon, Thibauld & Galas, Simon. (2017). Hazard study of medium-voltage switchgear with SF6 alternative gas
6. Wang, Jingqin & Wang, Li & Zhang, Guangzhi & Chi, Changchun. (2019). Study on prior information fusion method of low-voltage switchgear. Advances in Mechanical Engineering. 11. 168781401982667. 10.1177/1687814019826674.
7. Ma, Canpeng & Moesch, Gilles & Cabaret, Bertrand & Tobias, J.. (2012). Innovative MV switchgear for today's applications. 1-4. 10.1109/CICED.2012.6508711.
8. Ji, Tong & Xie, Wei & Wang, Xiaoqing & Zhang, Jinbo. (2017). The research of high voltage switchgear detecting unit. IOP Conference Series: Materials Science and Engineering. 222. 012021. 10.1088/1757-899X/222/1/012021.
9. Djekic, Z.: ‘Online circuit breaker monitoring system’. Master thesis, University of Novi Sad, Serbia, December 2007.

10. Goh, Hui Hwang & Sim, Sy & Hamzah, Nur & Mazlan, Sulaiman & Ling, Chin & Chua, Qing & Goh, Kai Chen. (2017). Types of Circuit Breaker and its Application in Substation Protection. Indonesian Journal of Electrical Engineering and Computer Science. 8. 213-220. 10.11591/ijeecs.v8.i1.pp213-220
11. Yu, Zhanqing. (2018). Temperature Rise Test and Analysis of High Current Switchgear in Distribution System. The Journal of Engineering. 2019. 10.1049/joe.2018.8371
12. Y. Nakano, M. Kozako, M. Hikita, T. Tanaka and M. Kobayashi, "Estimation of Internal Pressure of Vacuum Interrupter by Measuring Partial Discharge Current," 2018 28th International Symposium on Discharges and Electrical Insulation in Vacuum (ISDEIV), Greifswald, 2018, pp. 611-614, doi: 10.1109/DEIV.2018.8537045.
13. "Methods for Arc-Flash Prediction in Medium Voltage and Low Voltage Switchgear" Ghulam Amjad Hussain ,Aalto University publication series DOCTORAL DISSERTATIONS 221/2015.
14. "Switchgear Condition Monitoring" M. Budyn , H. M. Karandikar , M. G. Urmson ABB Corporate Research1 (PL), ABB Inc.2,3 (USA) CIGRÉ Canada 21, rue#39; Artois, F-75008 PARIS CIGRE-115 Conference on Power Systems [http : //www.cigre.org](http://www.cigre.org) Vancouver, October 17- 19, 2010..
15. "Modular online monitoring system to allow condition-based maintenance for medium voltage switchgear" Kevin Perdon 1, Massimo Scarpellini 2, Stefano Magoni 3, Luca Cavalli 4 ABB S.p.A., Via Friuli4, 24044 Dalmine (BG), Italy, 24th International Conference & Exhibition on Electricity Distribution (CIRED) 12-15 June 2017.
16. A. M. Graham and M. Hodder, "Current methods for conducting an arc flash hazard analysis," Conference Record of the 2004 IEEE Industry Applications Conference, 2004. 39th IAS Annual Meeting., Seattle, WA, USA, 2004, pp. 1741-1748 vol.3,

doi: 10.1109/IAS.2004.1348706.

Osaka, Japan, 2020, pp. 130-134,

doi:

10.1109/ICCRE49379.2020.90964

79.

17. “An Effective Approach to Reducing Arc Flash Hazards in Power Systems” Xiaodong Liang, Senior Member, IEEE, Bagen Bagen, Senior Member, IEEE, and David Wenzhong Gao, Senior Member, IEEE