Grid-Tied Converter Design for Wind-Turbine Permanent Magnet Generators

Arjun K. Rao[1], Sanjana P. Thakur[2]
Assistant Professor, Professor
Department of Electrical and Renewable Energy Systems
Greenfield Technical University, India
***Email ID**: - Arjunkraoj8jj@yahoo.com, sanjanathakurppp@gmail.com*

ABSTRACT

The rapid growth of wind energy has intensified research interest in efficient and reliable grid integration techniques. Permanent Magnet Synchronous Generators (PMSGs) are widely adopted in modern wind turbines due to their high efficiency, compact size, and capability to operate without external excitation. However, the variable-speed operation of wind turbines necessitates the use of advanced grid-tied power converter systems to ensure high-quality power injection into the utility grid. This paper presents a comprehensive review of grid-tied converter design for wind-turbine PMSG systems. The study covers converter topologies, control strategies, grid synchronization techniques, power quality issues, and fault ride-through requirements. Emphasis is placed on back-to-back voltage source converters, multilevel converters, and emerging wide bandgap device-based solutions. Practical challenges related to harmonic mitigation, reactive power control, and compliance with grid codes are also discussed. The paper concludes with future research directions focusing on converter efficiency improvement, reliability enhancement, and intelligent control methods for large-scale wind energy integration.

***KEYWORDS: -** Wind energy, Permanent magnet synchronous generator, Grid-tied converter, Back-to-back converter, Power quality, Wind turbine control*

Page 97-110 © MANTECH PUBLICATIONS 2019. All Rights Reserved

INTRODUCTION

Wind energy has become one of the most prominent renewable energy sources worldwide due to its sustainability, declining installation cost, and technological maturity. The increasing penetration of wind power into modern electrical grids demands reliable power electronic interfaces capable of ensuring stable, efficient, and grid-compliant operation. Among various generator technologies, Permanent Magnet Synchronous Generators (PMSGs) have gained significant attention in variable-speed wind turbine systems.

PMSGs offer several advantages compared to doubly fed induction generators (DFIGs), including higher efficiency, absence of rotor copper losses, reduced maintenance, and better performance at low wind speeds. However, PMSG-based wind turbines require full-scale power converters to interface with the grid. These grid-tied converters play a critical role in regulating power flow, maintaining grid synchronization, and improving power quality.

The design of grid-tied converters for wind-turbine PMSGs involves multiple challenges such as handling variable input voltage and frequency, meeting grid code requirements, minimizing harmonic distortion, and ensuring high system reliability. With increasing wind farm capacities and stricter grid regulations, advanced converter architectures and control strategies have become essential.

This paper reviews the state-of-the-art grid-tied converter designs used in PMSG-based wind energy systems. Key converter topologies, control methods, and grid interaction issues are discussed in detail, providing useful insights for researchers and practicing engineers.

WIND TURBINE PMSG SYSTEM OVERVIEW

A wind turbine system based on a Permanent Magnet Synchronous Generator (PMSG) represents one of the most efficient configurations for modern variable-speed wind energy conversion. The primary components of such a system include the aerodynamic wind turbine rotor, mechanical drive train, electrical generator, power electronic conversion stage, control and protection unit, and the grid interconnection interface. Each of these components plays a crucial role in ensuring maximum energy extraction from the wind while maintaining grid compatibility and system reliability.

Page 97-110 © MANTECH PUBLICATIONS 2019. All Rights Reserved

The wind turbine rotor captures kinetic energy from the wind and converts it into mechanical torque. This torque is transmitted through the drive train, which may include a gearbox or may be implemented as a direct-drive system. In gearbox-based designs, the low rotational speed of the turbine rotor is stepped up to match the operating speed of the generator. In contrast, direct-drive PMSG systems eliminate the gearbox entirely, directly coupling the turbine rotor to a low-speed, high-pole-count generator. Direct-drive configurations reduce mechanical losses and maintenance requirements but generally increase generator size and cost.

The mechanical energy is converted into electrical energy by the PMSG. Since wind speed continuously varies, the generator operates over a wide range of rotational speeds, resulting in electrical output with variable voltage magnitude and frequency. To make this power suitable for grid injection, a full-scale power electronic converter is used between the generator and the grid. The converter system ensures decoupled control of generator operation and grid-side requirements, which is essential for efficient and stable wind power generation.

1. Operating Principle of PMSG

The operating principle of a Permanent Magnet Synchronous Generator is based on the interaction between the magnetic field produced by permanent magnets on the rotor and the rotating magnetic field generated by stator currents. The rotor magnets provide a constant excitation flux, removing the need for external field current or slip rings, which are commonly required in electrically excited synchronous machines. This feature significantly improves efficiency and reduces maintenance.

As the wind turbine rotor rotates, it drives the PMSG rotor at a speed determined by wind conditions. The rotating magnetic field of the permanent magnets induces a three-phase alternating voltage in the stator windings. The frequency and amplitude of this generated voltage are directly proportional to the rotor speed. At low wind speeds, the generator produces low-frequency, low-voltage output, while higher wind speeds result in increased voltage and frequency.

Due to this inherent variability, the electrical output of the PMSG cannot be directly connected to the utility grid, which operates at fixed voltage and frequency. Therefore, the generated AC power is first rectified and conditioned using power electronic converters. Advanced control

Page 97-110 © MANTECH PUBLICATIONS 2019. All Rights Reserved

techniques are employed on the generator-side converter to regulate electromagnetic torque and control generator speed. This allows the wind turbine to operate at its optimal tip-speed ratio, ensuring maximum power extraction across a wide range of wind speeds.

Additionally, PMSGs exhibit superior performance in partial-load conditions compared to induction generators. The absence of rotor copper losses and improved power density make them particularly suitable for offshore and large-scale wind turbine applications, where efficiency and reliability are critical.

2. Need for Full-Scale Converters

In PMSG-based wind energy systems, the use of full-scale power electronic converters is a fundamental requirement. Unlike Doubly Fed Induction Generator (DFIG) systems, where only a fraction of the total power flows through the converters, PMSG systems require converters rated for the entire generator power. This is primarily because the generator operates independently of grid frequency and voltage.

The full-scale converter enables complete electrical decoupling between the generator and the grid. This decoupling provides several significant advantages. First, it allows precise control of active power delivered to the grid regardless of wind speed fluctuations. Second, reactive power can be independently controlled, supporting grid voltage regulation and meeting modern grid code requirements without the need for external compensation devices.

Another important advantage of full-scale converters is improved fault ride-through capability. During grid disturbances such as voltage dips or short circuits, the converter can protect the generator from excessive currents and maintain controlled operation. This capability is essential for compliance with stringent grid connection standards, especially in high-penetration wind power scenarios.

Furthermore, full-scale converters facilitate advanced functionalities such as soft grid synchronization, harmonic mitigation, and frequency support. They also enable seamless integration of energy storage systems, which can further enhance grid stability. Although the use of full-rated converters increases system cost and complexity, the operational flexibility and enhanced grid support features make them a preferred solution for modern PMSG-based

Page 97-110 © MANTECH PUBLICATIONS 2019. All Rights Reserved

wind turbines.

GRID-TIED CONVERTER ARCHITECTURE

The grid-tied converter forms the electrical interface between the wind-turbine PMSG and the utility grid. Its main function is to convert the variable-frequency, variable-voltage power generated by the PMSG into fixed-frequency, grid-compliant electrical power. Among various converter configurations, the back-to-back voltage source converter (VSC) has emerged as the most widely adopted solution in modern PMSG-based wind energy systems due to its flexibility, robustness, and mature control techniques.

The back-to-back VSC architecture enables independent control of the generator and grid sides, which is particularly important in variable-speed wind turbine applications. By fully decoupling the mechanical and electrical dynamics from grid conditions, this converter topology allows the wind turbine to operate at optimal efficiency while simultaneously satisfying grid code requirements related to voltage, frequency, and power quality.

A typical grid-tied back-to-back converter is composed of two pulse-width modulated (PWM) converters connected through a common DC-link. Both converters are usually implemented using insulated gate bipolar transistors (IGBTs) or, in recent designs, wide bandgap semiconductor devices such as SiC MOSFETs.

1. Back-to-Back Converter Configuration

The back-to-back converter consists of three main components: the generator-side converter (GSC), the DC-link capacitor, and the grid-side converter (GrSC). Each component has a specific role in the overall energy conversion and control process.

The **generator-side converter (GSC)** is directly connected to the stator terminals of the PMSG. Its primary function is to control the generator electromagnetic torque and rotational speed. By adjusting the stator current components in the synchronous reference frame, the GSC enables precise control of active power extracted from the wind turbine. This allows implementation of maximum power point tracking (MPPT) algorithms, ensuring optimal energy capture over a wide range of wind speeds. In addition, the GSC helps limit generator currents during transient operating conditions, thereby protecting the generator from electrical

Page 97-110 © MANTECH PUBLICATIONS 2019. All Rights Reserved

stress.

The **DC-link capacitor** serves as an energy buffer between the generator-side and grid-side converters. It absorbs power fluctuations caused by wind speed variations and sudden changes in grid demand. A properly designed DC-link ensures stable voltage operation, reduces ripple content, and improves the dynamic response of the converter system. However, the DC-link capacitor is also one of the most stressed and failure-prone components, making its sizing and thermal management critical for long-term system reliability.

The **grid-side converter (GrSC)** interfaces the DC-link with the utility grid. Its main objective is to regulate the DC-link voltage while injecting high-quality current into the grid. Using vector control techniques synchronized with the grid voltage, the GrSC independently controls active and reactive power flow. This enables compliance with grid codes that require wind turbines to support grid voltage regulation, power factor control, and frequency response. Furthermore, the grid-side converter plays a key role during grid disturbances by limiting fault currents and supporting low-voltage ride-through operation.

The coordinated operation of the generator-side and grid-side converters allows smooth power transfer from the wind turbine to the grid. While the generator-side converter optimizes energy extraction, the grid-side converter ensures that the delivered power meets utility standards. This separation of control objectives is one of the major advantages of the back-to-back VSC topology, making it the preferred choice for medium- and large-scale PMSG wind turbine applications.




Figure 1 (conceptual): Block diagram of PMSG-based wind turbine with back-to-back grid-tied converter.

Page 97-110 © MANTECH PUBLICATIONS 2019. All Rights Reserved

2. DC-Link Design Considerations

The DC-link is a critical part of the grid-tied converter architecture in PMSG-based wind turbine systems. Positioned between the generator-side converter and the grid-side converter, the DC-link primarily consists of a capacitor or a bank of capacitors. Its main function is to act as an intermediate energy storage element, allowing smooth power transfer between two subsystems that operate under different dynamic conditions. The design of the DC-link significantly influences system stability, dynamic performance, and overall converter reliability.

One of the primary roles of the DC-link capacitor is to absorb instantaneous power mismatches between the generator and the grid. Wind speed variations cause rapid changes in mechanical input power, while grid-side power demand and control response may change at a different rate. Without adequate DC-link energy storage, these power imbalances would result in large voltage fluctuations, potentially leading to converter instability or overvoltage stress on semiconductor devices.

The **sizing of the DC-link capacitor** is therefore a crucial design consideration. A larger capacitance reduces DC voltage ripple and improves transient response during sudden wind gusts or grid disturbances. It also helps maintain stable DC-link voltage during fault ride-through events, such as grid voltage dips. However, increasing the capacitance results in higher cost, increased physical volume, and additional thermal stress. Electrolytic capacitors, commonly used due to their high energy density, also suffer from limited lifetime, making over-sizing an unfavorable option from a reliability standpoint.

Another important factor is **voltage ripple limitation**. Excessive ripple in the DC-link voltage can deteriorate the performance of the grid-side converter, increase current harmonics, and impose additional stress on switching devices. Typically, the allowable voltage ripple is restricted to a small percentage of the nominal DC-link voltage to ensure proper modulation and control margin. This requirement directly influences capacitor selection and parallel capacitor configurations.

The **dynamic behavior of the DC-link** also affects control system design. A poorly designed DC-link may introduce slow voltage dynamics or oscillations that complicate DC voltage

Page 97-110 © MANTECH PUBLICATIONS 2019. All Rights Reserved

regulation. Hence, coordination between DC-link capacitor sizing and grid-side converter control parameters is essential. In practice, designers often select the DC-link capacitance based on worst-case operating conditions, such as maximum power step changes or low-voltage ride-through scenarios.

Thermal management and aging characteristics of DC-link capacitors are additional concerns. Capacitors are sensitive to temperature rise caused by ripple currents, which can significantly reduce their operational lifespan. Advanced cooling solutions, use of film capacitors, and capacitor health monitoring techniques are increasingly being adopted to improve reliability in high-power wind turbine applications.

In recent converter designs, efforts are also directed toward **DC-link voltage optimization**, where higher DC-link voltages are used to reduce current levels and conduction losses. This approach, however, demands careful insulation design and device selection. Overall, the DC-link design represents a trade-off between electrical performance, cost, physical size, and long-term reliability, making it one of the most important aspects of grid-tied converter design for PMSG-based wind turbines.

CONVERTER TOPOLOGIES FOR GRID INTEGRATION

The choice of converter topology plays a crucial role in the performance, efficiency, and reliability of grid-tied PMSG-based wind turbine systems. Converter topology determines the quality of the injected grid current, switching losses, voltage stress on semiconductor devices, and overall system scalability. Over the past decades, several converter structures have been proposed and implemented to meet the increasing power ratings and stricter grid code requirements of modern wind energy installations.

While conventional two-level converters remain dominant in small- and medium-power wind turbines, multilevel converter topologies are increasingly preferred for high-power and offshore wind energy applications. Each topology presents a trade-off between complexity, cost, controllability, and power quality.

1. Two-Level Voltage Source Converter

The two-level voltage source converter (VSC) is the most commonly used topology in early

Page 97-110 © MANTECH PUBLICATIONS 2019. All Rights Reserved

and low-to-medium power PMSG wind turbine systems. It consists of six active semiconductor switches arranged in a three-phase bridge configuration, allowing the output voltage of each phase to switch between two discrete levels, typically +Vdc/2 and −Vdc/2.

One of the main advantages of the two-level VSC is its **simple structure and mature control methods**. Pulse Width Modulation (PWM) techniques such as sinusoidal PWM and space vector PWM are well established and relatively easy to implement. This simplicity leads to lower development cost, reduced control complexity, and ease of maintenance, making the topology attractive for onshore wind turbines with moderate power ratings.

However, as wind turbine capacity increases, several limitations of the two-level VSC become evident. At high power levels, the converter must operate at elevated switching frequencies to reduce harmonic distortion, which in turn increases switching losses and reduces overall efficiency. Additionally, the high voltage steps associated with two-level switching generate significant dv/dt stress, leading to electromagnetic interference (EMI) issues and increased stress on insulation systems.

Another drawback is the higher harmonic content in the output voltage and current, which necessitates the use of bulky grid filters. These filters increase system size and cost, and may introduce resonance issues if not properly designed. Due to these limitations, the two-level VSC becomes less suitable for large-scale wind turbine systems, particularly those rated in the multi-megawatt range.

2. Multilevel Converters

Multilevel converters have emerged as a promising alternative for grid-tied PMSG wind turbines, especially in high-power applications. By generating output voltages with multiple discrete levels, these converters significantly reduce voltage distortion, switching losses, and stress on power devices. As a result, multilevel converters enable higher voltage operation with improved efficiency and power quality.

The **Neutral Point Clamped (NPC) converter** is one of the most widely used multilevel topologies in wind energy systems. NPC converters divide the DC-link voltage into multiple levels using clamping diodes, allowing the output voltage to transition smoothly between

Page 97-110 © MANTECH PUBLICATIONS 2019. All Rights Reserved

levels. This reduces harmonic distortion and dv/dt stress. However, maintaining neutral point voltage balance is a key challenge, requiring advanced control strategies.

The **Flying Capacitor (FC) converter** uses capacitors to generate intermediate voltage levels. It offers redundancy in switching states, which can improve fault tolerance. Nevertheless, the requirement for a large number of capacitors and complex voltage balancing control increases system complexity and cost, limiting its industrial adoption in wind turbines.

The **Cascaded H-Bridge (CHB) converter** consists of multiple H-bridge cells connected in series, each supplied by an isolated DC source. CHB converters provide excellent scalability and modularity, making them suitable for high-voltage wind energy applications. Their modular nature simplifies maintenance and enhances fault tolerance. However, the need for isolated DC sources or complex transformer arrangements can be a practical limitation.

Overall, multilevel converters offer superior performance in terms of efficiency, power quality, and scalability compared to two-level VSCs. Their adoption in PMSG-based wind turbine systems continues to grow, driven by the demand for higher power ratings, reduced losses, and compliance with increasingly strict grid codes.

Table 1: Comparison of Converter Topologies

Topology	Advantages	Limitations
Two-level VSC	Simple, low cost	High harmonics
NPC	Lower THD, higher voltage	Neutral point balancing
CHB	Modular, scalable	Requires isolated DC sources

3. Matrix Converters

Matrix converters represent an alternative grid-tied power conversion approach for PMSG-based wind turbine systems, differing fundamentally from conventional voltage source converter architectures. Unlike back-to-back converters, matrix converters perform direct AC–AC power conversion without the use of an intermediate DC-link. This is achieved through an array of bidirectional power switches that directly connect the generator phases to the grid phases in a controlled manner.

Page 97-110 © MANTECH PUBLICATIONS 2019. All Rights Reserved

One of the most significant advantages of matrix converters is the **elimination of the DC-link capacitor**, which is often considered one of the weakest components in conventional converter systems due to aging and thermal stress. By removing this component, matrix converters can potentially offer improved reliability and reduced maintenance requirements, which is particularly attractive for offshore wind turbines where accessibility is limited. Additionally, the absence of bulky DC-link capacitors contributes to higher power density and more compact converter designs.

From an operational perspective, matrix converters allow **bidirectional power flow** and provide sinusoidal input and output currents with controllable power factor. Advanced modulation techniques enable independent control of generator-side currents and grid-side power, similar to back-to-back VSC systems. This makes matrix converters theoretically suitable for variable-speed PMSG wind turbines that require flexible power control.

Despite these advantages, the practical adoption of matrix converters in wind energy systems remains limited. One of the main challenges is their **complex control strategy**. Matrix converters require sophisticated modulation algorithms to avoid short circuits between input phases and open-circuit conditions at the output. This increases computational burden and places stringent requirements on control hardware and software reliability.

Another important limitation is the **restricted voltage transfer ratio**, which typically does not exceed approximately 0.86 of the input voltage. This constraint can limit the achievable output voltage, especially under low wind speed conditions, potentially reducing the operational range of the wind turbine. As a result, additional design considerations such as oversizing the generator or incorporating step-up transformers may be necessary.

Furthermore, matrix converters require a large number of bidirectional switches, increasing system complexity and cost. The lack of widespread industrial experience and limited availability of standardized components also pose challenges for large-scale deployment.

In recent years, research efforts have focused on overcoming these limitations through improved modulation methods, fault-tolerant switching schemes, and the use of wide bandgap semiconductor devices. While matrix converters offer promising features in terms of reliability

Page 97-110 © MANTECH PUBLICATIONS 2019. All Rights Reserved

and power density, they are currently more suitable for research and niche applications rather than mainstream grid-tied PMSG wind turbine systems.

CONTROL STRATEGIES FOR GRID-TIED CONVERTERS

Control of grid-tied converters is essential for efficient wind energy extraction and grid compliance.

1. Generator-Side Control

The generator-side converter typically uses vector control or direct torque control. The main objective is to extract maximum power from the wind by maintaining optimal tip-speed ratio.

2. Grid-Side Control

The grid-side converter regulates DC-link voltage and controls active and reactive power exchange with the grid. A synchronous reference frame (dq) control is commonly employed.

3. Grid Synchronization

Phase-Locked Loop (PLL) techniques are used to synchronize the converter with grid voltage. Accurate synchronization ensures stable power transfer and reduces harmonic injection.

POWER QUALITY AND HARMONIC ISSUES

Grid-tied wind energy systems must comply with stringent power quality standards.

1. Harmonic Distortion

Switching actions of converters introduce harmonics into grid currents. Use of L or LCL filters is common to mitigate harmonics.

2. Reactive Power Control

Modern grid codes require wind turbines to support reactive power and voltage regulation. Grid-side converters enable dynamic reactive power control without additional hardware.

FAULT RIDE-THROUGH CAPABILITY

Low Voltage Ride-Through (LVRT) is a critical requirement for grid-connected wind turbines. During grid faults, the converter must remain connected and support grid recovery. DC-link overvoltage protection, current limiting strategies, and crowbar circuits are commonly used.

USE OF WIDE BANDGAP DEVICES

The adoption of SiC and GaN devices in grid-tied converters is increasing.

Page 97-110 © MANTECH PUBLICATIONS 2019. All Rights Reserved

1. Advantages

Wide bandgap devices offer higher switching frequency, lower losses, and improved thermal performance, leading to compact converter designs.

2. Challenges

High device cost and electromagnetic interference issues remain as practical challenges.

RELIABILITY AND THERMAL CONSIDERATIONS

Converter reliability significantly affects wind turbine availability.

Thermal stress, capacitor aging, and semiconductor degradation are major failure causes. Advanced cooling techniques and condition monitoring systems are being explored to enhance reliability.

FUTURE TRENDS AND RESEARCH DIRECTIONS

Future grid-tied converter designs will focus on:

- Modular and scalable architectures
- AI-based adaptive control strategies
- Improved fault tolerance
- Hybrid AC/DC grid compatibility

Integration of energy storage with wind converters is also emerging as a promising solution for grid stability.

CONCLUSION

Grid-tied converters are a critical component in PMSG-based wind energy systems, enabling efficient power conversion, grid compliance, and reliable operation. This paper reviewed converter architectures, control strategies, and key challenges associated with grid integration of wind turbines using PMSGs. Back-to-back voltage source converters remain the most widely used solution due to their flexibility and mature control techniques. However, multilevel converters and wide bandgap devices are gaining attention for high-power applications. Despite significant advancements, challenges related to power quality, fault ride-through, and long-term reliability persist. Continued research in advanced converter topologies, intelligent control, and thermal management will be essential for achieving higher penetration of wind energy in future power systems.

Page 97-110 © MANTECH PUBLICATIONS 2019. All Rights Reserved

REFERENCES

1. Heier, S., *Grid Integration of Wind Energy Conversion Systems*, Wiley, 2014.
2. Chen, Z., Guerrero, J. M., and Blaabjerg, F., "A review of grid-connected converters for wind power systems," *IEEE Transactions on Power Electronics*, 2009.
3. Li, H., and Chen, Z., "Overview of different wind generator systems and their comparisons," *IET Renewable Power Generation*, 2008.
4. Ackermann, T., *Wind Power in Power Systems*, John Wiley & Sons, 2012.
5. Teodorescu, R., Liserre, M., and Rodriguez, P., *Grid Converters for Photovoltaic and Wind Power Systems*, Wiley, 2011.
6. Blaabjerg, F., Ma, K., and Zhou, D., "Power electronics and reliability in renewable energy systems," *IEEE Journal of Emerging and Selected Topics in Power Electronics*, 2015.
7. Wu, B., *High-Power Converters and AC Drives*, Wiley-IEEE Press, 2006.
8. Yang, Y., Wang, H., and Blaabjerg, F., "Reliability of power electronic converters in renewable energy systems," *Renewable Energy*, 2014.
9. Qiao, W., Zhou, W., and Aller, J. M., "Wind speed estimation based sensorless control for PMSG wind turbines," *IEEE Transactions on Power Electronics*, 2013.
10. Singh, M., and Santoso, S., "Dynamic models for wind turbine generators," *IEEE Power & Energy Society General Meeting*, 2011.

Page 97-110 © MANTECH PUBLICATIONS 2019. All Rights Reserved